
## Aisin AB60E, AB60F Transmission Operation Chart



		Planetary Driving Devices				<b>Planetary Holding Devices</b>				One-Way Clutches				
Shift Lever Position	Gear Position	Clutch (C1)	Clutch (C2)	Clutch (C3)	Clutch (C4)	Brake (B1)	Brake (B2)	Brake (B3)	Brake (B4)	Sprag (F1)	Sprag (F2)	Sprag (F3)	Sprag (F4)	Gear Ratio:1
Р	Park													n/a
R*	Reverse			On		On			On	Holding				3.061
N	Neutral													n/a
D	1st	On			On							Holding	Holding	3.333
	2nd	On			On			On		Holding	Holding		Holding	1.960
	3rd	On		On	On			On**		Holding			Holding	1.353
	4th*	On	On	On**	On			On**					Holding	1.000
	5th*	On**	On	On		On		On**						0.728
	6th*	On**	On			On**	On	On**						0.588
5	1st	On			On							Holding	Holding	3.333
	2nd	On			On			On		Holding	Holding		Holding	1.960
	3rd	On		On	On			On**		Holding			Holding	1.353
	4th*	On	On	On**	On			On**					Holding	1.000
	5th*	On**	On	On		On		On**						0.728
4	1st	On			On							Holding	Holding	3.333
	2nd	On			On			On		Holding	Holding		Holding	1.960
	3rd	On		On	On			On**		Holding			Holding	1.353
	4th*	On	On	On**	On			On**					Holding	1.000
3	1st	On			On							Holding	Holding	3.333
	2nd	On			On			On		Holding	Holding		Holding	1.960
	3rd	On		On	On	On***		On**		Holding			Holding	1.353
2	1st	On			On							Holding	Holding	3.333
	2nd	On			On		On***	On		Holding	Holding		Holding	1.960
1	1st	On			On				On***			Holding	Holding	3.333

<sup>\*</sup> Engine Braking Occurs

<sup>\*\*</sup> Operates but not related to power transmission
\*\*\* Operates during engine braking